

1 Remove from packaging

Contents:

- Business WLAN-Box
- Mains adaptor with 1.5 m cable
- 5 m Ethernet cable



2 Installation position

Connection with Ethernet cable (recommended)

During the initial installation, the Centro Business 3.0 and the Business WLAN-Box should be connected using an Ethernet connection (faster and more reliable).

Without Ethernet cable

Your devices must always have a Wi-Fi connection to the router during installation. Therefore, position them at a distance of no more than 5 meters.



3 Connect to Centro Business 3.0 WLAN

Ensure that your smartphone, tablet or PC is connected to the WLAN router that you wish to extend.



Please note:

During installation, VPN or ‘private browsing mode’ must not be active on your device.

4 Launch the installation wizard

Scan the QR code on the back of the Business WLAN-Box with a smartphone and follow the instructions on the screen.

URL: mesh.swisscom.ch



The installation wizard now guides you through the following steps:

- Possible optimisation of the WLAN settings and activation of the mesh function.
- Pairing and configuration of the Business WLAN-Box.

Please note:

You will need the router login password for the installation process. Your login details can be found in My Swisscom Business.

5 Final location

With Ethernet connection (recommended)

Wherever possible, connect the Business WLAN-Box and router using an Ethernet connection to benefit from optimum stability and high speeds.


Without Ethernet connection (through WLAN)

Ensure that the Business WLAN-Box is located where there is sufficient WLAN signal (at least 50%).



Check if the installation has worked

Following successful installation and final positioning, all LEDs should be steady white:



Meaning of the Status LED:

This LED indicates if the Business WLAN-Box is not in the optimal position:



LED flashing white = too close to router







LED red = too far from router



Repeat the steps for additional Business WLAN-Boxes

Up to three Business WLAN-Boxes can be connected to the Centro Business 3.0 and set up in any formation:



Please note:

If several devices are connected in chain formation using WLAN backhaul (= without an Ethernet connection), the data throughput rate is halved with each additional WLAN-Box!



Online help

For more information and term definitions, go to:

www.swisscom.ch/bwb-help